

# 4BZ6

## Semiremote-Cutoff Pentode

### 7-PIN MINIATURE TYPE

#### With Heater Having Controlled Warm-Up Time

The 4BZ6 is the same as the 6BZ6 except for the following items:

Heater Characteristics and Ratings (*Design-Maximum Values*):

Current . . . . .	0.450 ± 0.030	amp
Voltage (AC or DC) at heater current = 0.450 . . . . .	4.2	volts
Warm-up time (Average). . . . .	11	sec

# 4BZ7

## Medium-Mu Twin Triode

### 9-PIN MINIATURE TYPE

#### With Heater Having Controlled Warm-Up Time

The 4BZ7 is the same as the 6BZ7 except for the following items:

Heater Characteristics and Ratings (*Design-Center Values*):

Current . . . . .	0.600 ± 0.040	amp
Voltage (AC or DC) at heater current = 0.600 . . . . .	4.2	volts
Warm-up time (Average). . . . .	11	sec

# 4CB6

## Sharp-Cutoff Pentode

### 7-PIN MINIATURE TYPE

#### With Heater Having Controlled Warm-Up Time

The 4CB6 is the same as the 6CB6 except for the following items:

Heater Characteristics and Ratings (*Design-Center Values*):

Current . . . . .	0.450 ± 0.030	amp
Voltage (AC or DC) at heater current = 0.450 . . . . .	4.2	volts
Warm-up time (Average). . . . .	11	sec
Peak heater-cathode voltage:		
Heater negative with respect to cathode. . . . .	300 <sup>a</sup> max.	volts
Heater positive with respect to cathode. . . . .	200 <sup>b</sup> max.	volts

<sup>a</sup> The dc component must not exceed 200 volts.

<sup>b</sup> The dc component must not exceed 100 volts.

